



Breakouts

For low voltage 2, 3 and 4-core with or without shielding

FEATURES

- Made of polyolefin
- Coated with sealing adhesive

APPLICATION

- For sealing the crutches of paper and polymeric insulated cables up to 1 kV

2-core

Product name	Application range (mm) ²	Diameter cable inlet (mm) ¹		Diameter fingers (mm)		Pack pc	Part Number
		A	B	A	B		
302K333/S(S20)	4 – 25	28.0	9.0	12.0	4.1	20	D93040N001
302K224/S(S20)	35 – 150	48.0	32.0	22.0	7.0	20	D45696N001
302K466/S(S10)	185 – 300	86.0	42.0	40.0	16.0	10	127794N001

3-core

Product name	Application range (mm) ²	Diameter cable inlet (mm) ¹		Diameter fingers (mm)		Pack pc	Part Number
		A	B	A	B		
402W533/S(S10)	4 – 35	38.0	13.0	16.0	4.2	10	096434N001
402W516/S(S5)	35 – 150	63.0	22.0	26.0	9.0	5	337914N001
402W526/S(S5)	185 – 300	82.0	28.0	36.0	13.0	5	000938N001
402W248/S(S5)	–	115.0	45.0	52.0	22.0	5	452278N001

4-core

Product name	Application range (mm) ²	Diameter cable inlet (mm) ¹		Diameter fingers (mm)		Pack pc	Part Number
		A	B	A	B		
502K033/S(S15)	4 – 35	36.0	16.5	14.0	3.4	15	E00553N001
502K046/S(S5)	35 – 70	45.0	19.0	20.0	7.0	5	086694N001
502K016/S(S5)	70 – 150	60.0	25.0	25.0	9.0	5	C52918N001
502K026/S(S5)	185 – 300	90.0	31.0	33.0	13.5	5	C22917N001

6-core

Application range (mm) ²	Diameter cable inlet (mm)		Diameter large fingers (mm)		Diameter small fingers (mm)		Pack pc
	A	B	A1	B1	A2	B2	
–							
ON REQUEST	114	35	44.7	14	22.8	7	1

¹ A = as supplied, and B = after free recovery.

² Recommended application up to 80% of expanded size.

³ The screen is folded back towards the oversheath. If you wish the screen to go straight up through a finger, select a moulding for an additional core.