

**MOTOR INFORMATION SHEET**

Sheet 1 of 2

**DRIVEN EQUIPMENT DATA**

Name	Boom Conveyor		
ID(s)	KKS code : 00EAA10AF001, 00EAA20AF001		
Manufacturer	FUJI ELECTRIC		
Driven Equip Max Brake Load	480N · m	Horsepower (hp) or kW at Design Conditions	132kW

**MOTOR DATA – ALL MOTORS (check choices)**

<input checked="" type="checkbox"/> Horizontal, Foot mount	<input type="checkbox"/> Vertical	<input checked="" type="checkbox"/> Induction	<input type="checkbox"/> Synchronous
Manufacturer	FUJI ELECTRIC		
Model	Low voltage squirrel cage induction motor		
Outline/Wiring/Connection Drawing Numbers	TJB56-L3-OFF-C-EAA-E-DRD-0180		
Design Standard*	IEC standard	Nameplate: Volts	380 Phase 3 Hz 50
For NEMA Motors - Nameplate hp	NA	Service Factor	1.0
Locked-Rotor Code Letter	NA	NEMA Design Letter	NA
For IEC Motors - Nameplate kW	132		
Max Continuous Voltage (rated frequency)	418	Min Continuous Voltage (rated frequency)	342
Duty Type:	<input checked="" type="checkbox"/> Continuous	<input type="checkbox"/> Definite Time (minutes)	Full Load Speed (rpm) 1475
Full Load Current at Rated hp or kW (amps)	235A, 132kW		
Locked-Rotor Current (amps)	NA		
NEMA or IEC Enclosure	IP55(Outdoor use)	Frame Size	315M
IEC Cooling (IC Code)	IC411	IEC Mounting (IM Code)	IM B3
Design Ambient Temperature (°C)	40	Insulation System Class	Class-F, B rise
Temp Rise by Resistance (at service factor load) for NEMA Motor (°C)	NA		
Space Heaters (SP) Furnished?	<input checked="" type="checkbox"/> Yes	<input type="checkbox"/> No	Total SP Load: 100W Volts AC220 Phase 1
Bearings: Type	DE : 6322, NDE : NU216 , Grease replenishment type		
Lubrication Type	Bottun Head (ALVANIA RL2)	System	Individual manual
ABMA L-10 Rating Life, Not Less than	2,000	Hours	
Connection: (check one)	<input checked="" type="checkbox"/> Direct	<input type="checkbox"/> Belt	<input type="checkbox"/> Chain
Overall Mean No-Load Sound Pressure Level, re micro-pascals (0.0002 microbar), Reference Distance of 3 Feet	NA		Free Air
Total Motor Weight (lb)	1240kg	Is Motor Reversible?	<input type="checkbox"/> Yes <input checked="" type="checkbox"/> No
Multi-Connectable Motors: (check choices)	<input type="checkbox"/> Part Winding <input type="checkbox"/> Star-Delta <input type="checkbox"/> Variable Torque <input type="checkbox"/> Constant Torque <input type="checkbox"/> Constant Horsepower <input type="checkbox"/> PAM <input type="checkbox"/> Two Winding <input type="checkbox"/> One Winding <input type="checkbox"/> Other	NA	
rpm	FL Amps	LR Amps	rpm FL Amps LR Amps
rpm	FL Amps	LR Amps	rpm FL Amps LR Amps
For Motors in Hazardous Locations: Motor Enclosure Maximum Surface Temperature (°C)	NA		
Will Motor Contain a Surface Temperature Control Thermostat Requiring Connection into the Motor Starter Control Circuit?	<input type="checkbox"/> Yes	<input checked="" type="checkbox"/> No	
Motor Full-Load Efficiency as Defined by NEMA MG-1-2006 Tables 12-10, 12-11, and 12-12: (check one)	<input checked="" type="checkbox"/> Normal Efficiency IE1(IEC)	<input type="checkbox"/> Energy Efficient IE2(IEC)	<input type="checkbox"/> Premium Efficiency IE3(IEC)
	Full Load Nominal Efficiency Rating	NA	

\*NEMA, IEC, etc.

Painting specification : C5 or equivalent



**MOTOR INFORMATION SHEET**

**Sheet 2 of 2**

Name	Boom Conveyor
ID(s)	KKS code : 00EAA10AF001, 00EAA20AF001

**ADDITIONAL MOTOR DATA TO BE SUBMITTED**

**Motors 100 hp (75 kW) and Larger and for All Motors Rated Above 1000 Volts NA**

Efficiency, Percent Guaranteed, Load: 1/2		3/4		4/4	
Power Factor, Percent Guaranteed, Load: 1/2		3/4		4/4	
Power Factor at Locked Rotor Current					
Minimum Starting Voltage in Percent of Rated Voltage: Calculated	90%	Specified	90%		

Accelerating Time:

At Rated Voltage (seconds)	NA
At Minimum Specified Starting Voltage (seconds)	NA

Locked-Rotor Safe Stalled Time (seconds):

	Rated Voltage	Minimum Specified Starting Voltage
Motor Initially at Maximum Specified Ambient Temperature (Cold)		
Motor Initially at Service Factor Load Operating Temperature (Hot)		

**For All Motors Rated Above 1000 Volts NA**

Current and Torque Versus Speed Curves at Maximum, Rated, and Minimum Specified Starting Voltage.					
Drawing Number					(Attach curves.*)
Power Factor and Efficiency Versus Speed Curves at Rated Voltage.					
Drawing Number					(Attach curves.*)
Current Versus Time Curves at Maximum, Rated, and Minimum Specified Starting Voltage.					
Drawing Number					(Attach curves.*)
Locked-Rotor Thermal Limit Curves (current versus time), Curves in Both Cold and Hot Operating Conditions, and Stator Running Thermal Overload Curves at Rated Voltage.					
Drawing Number					(Attach curves.*)
Torque in: (check one)	<input type="checkbox"/> lb-ft	<input type="checkbox"/> N-meter			
Locked-Rotor Torque		Pull-up Torque		Breakdown Torque	
Inertia in: (check one)	<input type="checkbox"/> lb-ft <sup>2</sup>	<input type="checkbox"/> GD <sup>2</sup>			
Motor Rated		Motor Rotor		Driven Equipment	Coupling
Temperature Alarms and Trips for Motors Equipped with Sensors:					
Stator Winding RTD	Alarm (°C)		Trip (°C)		
Bearing Temperature	Alarm (°C)		Trip (°C)		
Motor Subtransient Reactance			Motor Open Circuit Time Constant		
Short-Circuit Time Constant			Starting Power Factor		

**Number of Successive Starts:**

	At Rated Voltage
Motor Initially at Maximum Specified Ambient Temperature (cold with driven equipment connected), number	3 times
Motor at Rated Temperature Rise Prior to Starting (hot with motor coupled), number	2 times
Cooling Period Required After Completion of the Preceding Maximum Number of Successive Starts Before Making Additional Starts, minutes	
Motor Stopped Cooling Time Constant, minutes	NA
Motor Running Cooling Time Constant, minutes	

**List of Drawings and Specifications:**

Lubrication Oils and Greases, drawings	NA
External Fluid Circuits for Bearing Cooling, drawings	NA
External Fluid Circuits for Stator Cooling, drawings	NA

\*Submit tabulated data with curves for high inertia loads.

